

PowerRouter Solar Inverter

generate and use your own solar energy

The PowerRouter Solar inverter is the perfect solution for all feed-in and self-use schemes. This compact, all-in-one system inverts the solar energy you generate and its integrated, web-based logging features allow you to remotely monitor your self-generated power. Thanks to its “connect & grow” capability, the PowerRouter can be easily expanded with batteries for storing energy. Not only does this provide backup during a power outage, it also allows you to optimize the use of your self-generated power during normal operation.



- available in 5.0kW, 3.7kW and 3.0kW versions
- compatible with all modern PV technologies, including thin film
- 2 fully independent MPP trackers
- back-up power supply (“Local Out”)
- easy installation with built-in wizard
- integrated web-based monitoring & management

maximize your output

Maximize the yield of your solar generation system by selecting the most cost-effective energy mode, either feeding into the grid or directly using your self-generated energy (self-use).

The system has two wide-range inputs with fully independent MPP trackers to maximize yield and system configuration flexibility. This feature can accommodate two separate solar arrays at maximum string length and minimum installation costs.

backup power supply

The PowerRouter Solar Inverter has a unique feature: it supplies backup power in the event of a grid failure. Unlike other inverters, the PowerRouter switches to “island mode” when the grid fails. After a short delay it resumes operation, enabling its unique “Local Out” connection to supply a stable 230Vac power signal to your connected loads. This backup works as long as there is sufficient solar power. For full backup, even at night, the PowerRouter can be easily expanded with a Battery Manager (“connect & grow”).

monitor & manage

When the PowerRouter is connected to the internet, the web portal myPowerRouter.com gives detailed system information (e.g. performance, profit, solar yield) on each PowerRouter unit. The PowerRouter can even be remotely updated with new firmware containing the latest features, so your system is always up to date.

| Grid |
|--|
| Continuous output power at 40 °C (P nom) |
| AC output current |
| AC output voltage (nominal) |
| AC output range |
| Protection |
| Standby losses |
| User interface |
| Connectivity |
| Backup switch over time |

| PR50S/S0 | PR37S/S0 | PR30S/S0 |
|--|------------------------------|----------|
| 5000 Wac (4600 Wac DE) | 3700 Wac (3680 Wac DE/UK/PT) | 3000 Wac |
| 22A | 16A | 13A |
| 230 Vac ± 2%, 50 Hz ± 0.2%, true sine wave <3% THD, single phase | | |
| 180-264 Vac 45-55 Hz (limited by local anti-islanding regulations) | | |
| electronic, fused | | |
| ≤ 4W | | |
| interactive display with 4-button operation | | |
| ethernet RJ45, TCP/IP | | |
| <1 second | | |

| Solar |
|-------------------------|
| Max. Input |
| No. of strings |
| No. of MPP trackers |
| DC Disconnection switch |
| Solar Voltage |
| MPP Voltage |
| Solar Connections |
| Max. Efficiency |
| Max. MPP Efficiency |

| PR50S/S0 | PR37S/S0 | PR30S/S0 |
|-----------------------------|---------------------------|-------------------|
| 5.5 kWp and 15 A per string | 4 kWp and 15 A per string | 3.3 kWp 15 A |
| 2 | 2 | 1 |
| 2, fully independent | 2, fully independent | 1 |
| 4-pole, 600V, 15A | 4-pole, 600V, 15A | 2-pole, 600V, 15A |
| 150 – 600 Vdc per string | | |
| 100 – 480 Vdc per string | | |
| MC4 | | |
| 94.5% | | |
| 99.9% | | |

| Environmental |
|--|
| Operating Temperature Range (full power) |
| Storage Temperature |
| Humidity |
| Regulatory Approvals and Standards |
| Safety |
| Emission |
| Immunity |
| Anti Islanding Protection |
| Warranty |

| PR50S/S0 | PR37S/S0 | PR30S/S0 |
|---|----------|----------|
| -10 °C to +50 °C (derating from 40 °C) | | |
| -40 °C to +70 °C | | |
| maximum 95%, non-condensing | | |
| CE | | |
| EN 60950-1, EN 62109-1 | | |
| EN 55014-1, EN 61000-3-2, EN 61000-3-3, EN 61000-6-3 | | |
| EN 55014-2, EN 61000-6-2 | | |
| VDE 0126.1.1, G83/1(UK), RD1663/2000(ESP), DK5940 E.d. 2.2 (IT), AS4777(AUS) | | |
| (check www.PowerRouter.com for other country certifications) | | |
| five years (optional: extension to ten years) | | |

| General |
|---------------------|
| Dimensions (WxHxD) |
| Protection Category |
| Weight |
| Topology |
| Cooling |

| PR50S/S0 | PR37S/S0 | PR30S/S0 |
|-------------------------------|----------|----------|
| 545 x 502 x 149 mm | | |
| IP 21 | | |
| 15.5 kg | | |
| galvanic isolated transformer | | |
| forced airflow | | |

Connect & Grow Options

PowerRouter Solar Inverter + Battery Manager



All specifications are subject to change without prior notice © Copyright 2012